

OPHIR OPTRONICS SOLUTIONS LTD.

Laser Power & Energy Meter

- Nova II

Thermopile Head

Supported version TOP Design Studio V1.4.9.76 or higher



CONTENTS

We want to thank our customers who use the Touch Operation Panel.

- 1. System configuration** [Page 2](#)
Describes connectable devices and network configurations.
- 2. External device selection** [Page 3](#)
Select a TOP model and an external device.
- 3. TOP communication setting** [Page 4](#)
Describes how to set the TOP communication.
- 4. Cable table** [Page 9](#)
Describes how to set up communication for external devices.
- 5. Supported addresses** [Page 10](#)
Describes the available address that can communicate with an external device.

1. System configuration

The system configuration of TOP and "Ophir – Laser Power & Energy Meter" is as follows:

Series	Sensor (head) ^{*Note 1)}	Link I/F	Communication method	System setting	Cable
Nova II	Thermopile	RS-232C I/O Port	RS-232C	3. TOP communication setting	4 Cable table

*Note 1) Sensor (Head) only supports the Thermopile head.


■ Connection configuration

- 1:1 (one TOP and one external device) connection – configuration which is possible in RS232C communication.



2. External device selection

- Select a TOP model and a port, and then select an external device.



Settings		Contents					
TOP	Model	Check the display and process of TOP to select the touch model.					
External device	Vendor	Select the vendor of the external device to be connected to TOP. Select "Ophir Optronics Solutions Ltd."					
	PLC	Select an external device to connect to TOP. <table border="1" style="width: 100%; margin-top: 10px;"> <thead> <tr> <th>Model</th> <th>Interface</th> <th>Protocol</th> </tr> </thead> <tbody> <tr> <td>Laser Power Meter</td> <td>Serial</td> <td>PowerMeterComm</td> </tr> </tbody> </table>	Model	Interface	Protocol	Laser Power Meter	Serial
Model	Interface	Protocol					
Laser Power Meter	Serial	PowerMeterComm					

3. TOP communication setting


The communication can be set in TOP Design Studio or TOP main menu. The communication should be set in the same way as that of the external device.

3.1 Communication setting in TOP Design Studio

(1) Communication interface setting

■ [Project > Project Property > TOP Setting] → [Project Option > "Use HMI Setup" Check > Edit > Serial]

– Set the TOP communication interface in TOP Design Studio.



Items	TOP	External device	Remarks
Signal Level (port)	RS-232	RS-232	
Baud Rate		9600	
Data Bit		8	
Stop Bit		1	
Parity Bit		None.	


* The above settings are examples recommended by the company.

Items	Description
Signal Level	Select the serial communication method between the TOP and an external device.
Baud Rate	Select the serial communication speed between the TOP and an external device.
Data Bit	Select the serial communication data bit between the TOP and an external device.
Stop Bit	Select the serial communication stop bit between the TOP and an external device.
Parity Bit	Select the serial communication parity bit check method between the TOP and an external device.

(2) Communication option setting

■ [Project > Project Property > Device Setting > COM > "PLC1: Laser Power Meter"]

– Set the options of the Ophir Laser Power Meter communication driver in TOP Design Studio.




Items	Settings	Remarks
Interface	Select "Serial".	Refer to "2. External device selection".
Protocol	Select "PowerMeterComm".	
TimeOut (ms)	Set the time for the TOP to wait for a response from an external device.	
SendWait (ms)	Set the waiting time between TOP's receiving a response from an external device and sending the next command request.	
Retry	Configures the number of attempts for communication upon failure.	

3.2. Communication setting in TOP


* This is a setting method when "Use HMI Setup" in the setting items in "3.1 TOP Design Studio" is not checked.

- Touch the top of the TOP screen and drag it down. Touch "EXIT" in the pop-up window to go to the main screen.



(1) Communication interface setting

- [Main Screen > Control Panel > Serial]




Items	TOP	External device	Remarks
Signal Level (port)	RS-232	RS-232	
Baud Rate		9600	
Data Bit		8	
Stop Bit		1	
Parity Bit		None.	

* The above settings are setting examples recommended by the company.

Items	Description
Signal Level	Select the serial communication method between the TOP and an external device.
Baud Rate	Select the serial communication speed between the TOP and an external device.
Data Bit	Select the serial communication data bit between the TOP and an external device.
Stop Bit	Select the serial communication stop bit between the TOP and an external device.
Parity Bit	Select the serial communication parity bit check method between the TOP and an external device.

(2) Communication option setting

■ [Main Screen > Control Panel > PLC]



Items	Settings	Remarks
Interface	Select "Serial".	Refer to "2. External device selection".
Protocol	Select "PowerMeterComm".	
TimeOut (ms)	Set the time for the TOP to wait for a response from an external device.	
SendWait (ms)	Set the waiting time between TOP's receiving a response from an external device and sending the next command request.	
Retry	Configures the number of attempts for communication upon failure.	

3.3 Communication diagnostics

- Check the interface setting status between the TOP and an external device.
 - Touch the top of the TOP screen and drag it down. Touch "EXIT" in the pop-up window to go to the main screen.
 - Check if the COM port settings you want to use in [Control Panel > Serial] are the same as those of the external device.

- Diagnosis of whether the port communication is normal or not
 - Touch "Communication diagnostics" in [Control Panel > PLC].
 - The Diagnostics dialog box pops up on the screen and determines the diagnostic status.

OK	Communication setting normal
Time Out Error	Communication setting abnormal - Check the cable, TOP, and external device setting status. (Reference: Communication diagnostics sheet)

- Communication diagnostics sheet
 - If there is a problem with the communication connection with an external terminal, please check the settings in the sheet below.

Items	Contents	Check		Remarks	
System configuration	How to connect the system	OK	NG	1. System configuration	
	Connection cable name	OK	NG		
TOP	Version information	OK	NG	2. External device selection 3. Communication setting	
	Port in use	OK	NG		
	Driver name	OK	NG		
	Other detailed settings	OK	NG		
	Relative prefix	Project setting	OK		NG
		Communication diagnostics	OK		NG
	Serial Parameter	Transmission Speed	OK		NG
Data Bit		OK	NG		
Stop Bit		OK	NG		
Parity Bit		OK	NG		
External device	CPU name	OK	NG	4. External device setting	
	Communication port name (module name)	OK	NG		
	Protocol (mode)	OK	NG		
	Setup Prefix	OK	NG		
	Other detailed settings	OK	NG		
	Serial Parameter	Transmission Speed	OK		NG
		Data Bit	OK		NG
		Stop Bit	OK		NG
Parity Bit		OK	NG		
Check address range	OK	NG	6. Supported addresses (For details, please refer to the PLC vendor's manual.)		

4. Cable table

This chapter introduces a cable diagram for normal communication between the TOP and the corresponding device.
(The cable diagram described in this section may differ from the recommendations of "Ophir – Laser Power & Energy Meter")

- Use RS-232C NOVA-II cable (P/N 7E1206)

5. Supported addresses

The devices available in TOP are as follows:

The device range (address) may differ depending on the CPU module series/type. The TOP series supports the maximum address range used by the external device series. Please refer to each CPU module user manual and be take caution to not deviate from the address range supported by the device you want to use.

Device (Type/Size)	Description (Read-only)
POWER (Float / 32Bit)	Measured power value
ENERGY (Float / 32Bit)	Measured energy value
POWER_CHECK (/ 1Bit)	Check whether power measurement is in progress
ENERGY_CHECK (/ 1Bit)	Check whether energy measurement is in progress